marantz





AV8805

13.2 CHANNEL PRE-AMPLIFIER SETS A NEW STANDARD IN HOME CINEMA OFFERING MAXIMUM VERSATILITY AND CONNECTIVITY

With 13.2 channel processing, the Marantz AV8805 supports virtually any high-resolution multichannel audio format, including the latest surround formats Dolby Atmos, DTS:X and Auro-3D. And our unique Marantz-own current feedback HDAMs enhance music for a superior listening experience.

Highlights	Your Benefits			
13.2 Channel Home Cinema Experience	Provides a flexible yet detailed pre-amplifier stage for the home cinema enthusiast. Enjoy it with matching Marantz MM series power amplifiers, like the MM8077.			
Supports Latest 3D Audio Formats	Enjoy immersive, three-dimensional sound with the latest surround formats including Dolby Atmos (up to 7.1.6 or 9.1.4 DTS:X and Auro-3D (up to 13.1)			
HDAM Discrete Buffer Amplifier Modules	Unique HDAM technology combines matched-precision discrete circuit elements with ultra-wide-end response for a wider soundstage and refined musical reproduction.			
Built-in Bluetooth, Wi-Fi and AirPlay Capability	Built-in Bluetooth and Wi-Fi with 2.4GHz/5GHz dual band support offer improved network stability even in Wi-Fi-crowded home			
HEOS	Stream music from TuneIn Internet radio, Pandora, Spotify, SiriusXM, Amazon Prime Music, TIDAL and more via the HEOS app.			
High-Resolution Audio Support	High-performance 192kHz/32bit D/A converters for all channels provide the highest resolution for music and movies.			
Smart TV Connectivity	The AV8805 can be controlled with your Smart TV remote via the HDMI CEC functionality associated with your Smart TV.			
Latest HDMI Connectivity; HDCP 2.2 Compatible; ISF-Certified	Ultimate visual quality with 4K/60 Hz full-rate pass-through, 4:4:4 color resolution, HDR, BT.2020, Dolby Vision and HLG (Log Gamma) pass-through. Eight HDMI inputs, including one on the front, with full HDCP 2.2 support, plus three HDMI out (zone) and plenty of inputs for your digital and analog legacy devices and the ability to support different video in different			
Advanced multi-room options; 15.2ch pre-out; RS232 control; Crestron connected, IP-control	Audio and video in multiple rooms; ready for third-party home automation systems.			
Premium-grade AK4490 32-bit D/A converters on all channels; Balanced XLR stereo input; 15.2ch balanced XLR and RCA outputs				
Most Advanced Audyssey Room Correction Suite	With the full Audyssey Platinum suite of advanced DSP algorithms, the AV8805 features Audyssey MultEQ XT32 automatic room acoustic correction. With the supplied measurement microphone, MultEQ XT32 analyzes each speaker's output (including the subwoofers) at up to 8 measurement locations and generates precision digital filters that optimize each channel for the correct frequency and time domain response. Plus, the optional Audyssey MultEQ Editor app lets you view and adjust settings for detailed tuning and customize the sound more precisely to your room and tastes.			















































marantz

AV8805

13.2 CHANNEL NETWORK PRE-AMPLIFIER WITH HEOS MUSIC STREAMING TECHNOLOGY





FEATURES	AV8805			
MULTICHANNEL SURROUND	A10003			
DTS HD Master / DTS:X / DTS Neural:X	• / • / •			
Dolby TrueHD / Dolby Atmos / Dolby Surround	• / • / •			
Auro-3D / Auromatic	• / •			
Multichannel Stereo	•			
Compressed audio enhancer: MDAX2	•			
Audyssey	MultEQ XT32 with LFC/Sub EQ HT			
Audyssey Dynamic EQ / Dynamic Volume	• / •			
Audyssey MultEQ Editor App support	•			
NETWORK	•			
Network Audio Streaming	•			
HEOS Multiroom integrated	•			
	•			
Lossy formats MP3 / WMA / AAC Lossless formats FLAC / ALAC / WAV	•/•/•			
DSD Streaming	• / • / •			
FLAC HD 192/24 / WAV 192/24 / ALAC 192/24	• (2.8 MHz / 5.6 MHz) • / • / •			
Gapless playback	• (FLAC, WAV, ALAC, DSD)			
AirPlay audio streaming	•			
Internet Radio (TuneIn)	•			
Spotify Connect / Deezer / TIDAL / Napster / Pandora / Amazon Music / Soundcloud*	•/•/•/•/•/•			
Compatible with Remote APP for Smart Phones	Android/iOS			
Ethernet / Wi-Fi	• / • (dual antenna / dual band)			
USB Audio / Made for iPod / Made for iPhone	• / AirPlay / AirPlay			
Bluetooth	•			
HDMI				
4K 60Hz 4:4:4 resolution / HDCP 2.2 / HDR / BT.2020	• / • / • / •			
eARC (Enhanced Audio Return Channel)	•			
Dolby Vision compatible / Hybrid Log Gamma (HLG)	• / •			
HDMI pass through on stand-by	•			
3D video pass through	•			
Video conversion	CVBS / HDMI; Comp / HDMI			
Videoprocessing and -scaling	1080p, 4K 60/50Hz			
INPUTS/OUTPUTS				
Composite In / Out	4+1 / 2 (main + zone)			
Component In / Out	3/1			

* This feature	is not	available	in al	Lountries.
Tillo Touturo	10 1100	avanabic	III GI	countries.

Sound United 1 Viper Way Vista, CA 92081

AUDI)				
Analo	g In / Out		7 + 1x Phono + 1x XLR / 0		
Digita	Optical In		2		
Digita	Coaxial In		2		
Multic	hannel Pre-out		• (15.2ch with 13.2 processing)		
Zone a	udio Pre-out	e-out 2			
Subwo	ofer Out		2		
7.1 M	ıltichannel input		•		
OTHE	RS				
Auto S	peaker Setup by Mi	crophone	•		
FL Dis	olay		•		
Graph	c User Interface - Gl	JI	Advanced		
ISF Ce	rtification		•		
GUI La	nguages		3		
Setup	Assistant		•		
Smart	Assistant		•		
Firmw	are Update by Netw	ork / USB	• / •		
Variab	le Cross Over		•		
Optim	zed Bass Redirectio	n	•		
Bass Sync			•		
ECO Mode			•		
Auto Power off			•		
Sleep Timer			•		
GENE	RAL				
Availa	ble colors: Black				
System Remote Control			RC039SR		
Power	Consumption in W		90		
Stand	y Consumption in V	/	0.2 (with CEC 0.5)		
Maxin	Maximum Dimensions (W x D x H) in IN		17.3 x 16.1 x 7.3		
Weight in lbs			30.2 lbs		
UPC					
NA	AV8805/U1B	699927151355	Black		

because music matters

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the DTS in combination with the Symbol, DTS-X, and the DTS-X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: www.spotify.com/connect/third-party-licenses. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

^{*} All specs can be subject to change.